

PTS 3.3 *genX*

Three-phase, fully automatic test system with class 0.05 reference standard and integrated three-phase current and voltage source



The PTS 3.3 genX portable test system consists of an integrated three-phase current and voltage source unit and a three-phase electronic reference standard of accuracy class 0.05. Characteristic features of the PTS 3.3 genX are its wide measuring range, high accuracy and high tolerance to unwanted external influences.

The PTS 3.3 genX allows the monitoring of meter installations as well as analysis of the local mains conditions.

Advantages

- Easy verification of meters under precise load conditions, using the built-in, compact, current and voltage source
- Automatic operation with predefined load points without the need for an external PC
- Large 9" (800 x 480 pixels) TFT touch screen colour display with graphical user interface
- Data transfer and communication via USB (Type B), ETHERNET or WLAN
- Built in web server for remote display of graphical user interface and remote control of the unit
- Data storage on removable SD memory card
- Two USB (type A) connectors for connection of peripherals like mouse, keyboard

Functions

- Independent generation of single- or three-phase loading conditions for verification of meters
- Active, reactive and apparent energy measurement for three phase, 3 or 4-wire, systems with integrated error calculator with 2 pulse inputs (1 configurable as output)
- Vector diagram, harmonics spectrum, wave form and rotary field display for analysis of the mains conditions
- Burden measurement of Current Transformer (CT) and Potential Transformer (PT)
- Ratio testing of Current Transformers (CT)

Options

- Software CAIntegration
- UCT 120.3 set of 3 clamp-on CT's 120 A
- UCT 1000.3 set of 3 clamp-on CT's 1000 A
- UCT LEM.3 set of 3 flexible current probes FLEX 3000 (30/300/3000A)
- UCT AMP-LiteWire 3-phase adapter set for AmpLiteWire + primary high voltage current sensor AmpLiteWire 2000 A
- UCT VOLT-LiteWire 3-phase adapter set for VoltLiteWire + primary voltage sensor VoltLiteWire 40 kV

Technical Data PTS 3.3 *genX*

General

Auxiliary power supply:	88 VACmin ... 264 VACmax / 47 ... 63 Hz Protection: Switch off supply at > 276 VAC
Power consumption:	max. 500 VA
Housing:	Hard Plastic
Dimensions:	W 470 x D 320 x H 253 mm
Weight:	approx. 23 kg
Operation temperature:	-10 °C ... +50 °C
Storage temperature:	-20 °C ... +60 °C
Relative humidity:	≤ 85% at Ta ≤ 21°C ≤ 95% at Ta ≤ 25°C, 30 days / year spread

Safety

CE

Isolation protection:	IEC 61010-1:2010
Measurement Category:	300V CAT III, 600V CAT II
Degree of protection:	IP-40

Power Source - Ranges

Voltage Range	30 V ... 480 V		
Output power	30 VA (per phase)		
	Internal Ranges	S_{max} / I_{max}	
	30 V ... 60 V	30 VA /	0.5 A
	60 V ... 120 V	30 VA /	0.25 A
	120 V ... 240 V	30 VA /	0.125 A
	240 V ... 480 V	30 VA /	0.0625 A
Current Range	1 mA ... 120 A		
Output power	60 VA (per phase)		
	Internal Ranges	S_{max} / U_{max}	
	1 mA ... 12 mA	60 mVA /	5 V
	12 mA ... 120 mA	600 mVA /	5 V
	120 mA ... 1.2 A	6 VA /	5 V
	1.2 A ... 12 A	60 VA /	5 V
	12 A ... 80 A	60 VA /	0.75 V
	80 A ... 120 A	60 VA /	0.5 V

Power Source - Accuracy

Resolution U, I	0.01 % of end of internal range		
Accuracy U, I	≤ 0.1 % of end of internal range		
Distortion Factor U, I	≤ 0.25 % on linear load		
Stability U, I	≤ 0.03 % (30 min.) ≤ 0.1 % (1 h)		
Load Regulation U, I	≤ 0.01 % (from 0 % ... 100 % load)		
Power Factor of Load	0.5 cap - 1 - 0.1 ind		
Bandwidth U, I	30 Hz ... 3 kHz (-3 dB)		
Efficiency U, I	> 85 %		
	Range	Accuracy	Resolution
Phase Angle	-180° ... +180°	± 0.1°	0.01°
Frequency	40 Hz-70 Hz	± 0.01 Hz	0.01 Hz
Mode Sync (to input voltage)	40 Hz-70 Hz		

Reference Standard - Measurement Ranges

Measuring Quantity	Range	Input / Sensor
Voltage (phase - neutral)	5 V ... 500 V 10 mV ... 5 V	U1, U2, U3 U1, U2, U3 (Burden)
Current	1 mA ... 12 A 1 mA ... 120 A 10 mA ... 120 A 100 mA ... 1000 A 3 A ... 3000 A	12 A (I1, I2, I3) 120 A (I1, I2, I3) UCT 120.3 UCT 1000.3 FLEX 3000

Reference Standard - Measurement Accuracy

Voltage / Current		≤ ± E [%] ^{1 2 4}
Measuring Quantity	Range	Class 0.05
Voltage (U1, U2, U3, N)	30 V ... 500 V 5 V ... 30 V	0.05 0.1
Current direct 12 A / 120 A	10 mA ... 120 A 1 mA ... 10 mA	0.05 0.1
Current CT 120A UCT 120.3	100 mA ... 120 A 10 mA ... 100 mA	0.2 1.0
Current CT 1000A UCT 1000.3	10 A ... 1000 A 1 A ... 10 A	0.2 1.0
Current FLEX 3000 UCT LEM.3	300 A ... 3000 A 30 A ... 300 A 3 A ... 30 A	0.1 + E _M
Burden Voltage (U1)	500 mV ... 5 V 10 mV ... 500 mV	0.5 0.5

Power / Energy	Voltage: 30 V ... 500 V (U - N)	≤ ± E [%] ^{1 2 3}
Measuring quantity / Input I	Range	Class 0.05
Active (P), Apparent (S) and Reactive (Q) Power / Energy		
Direct 12 A / 120 A (I1, I2, I3)	10 mA ... 120 A 1 mA ... 10 mA	0.05 0.1
Current CT 120A UCT 120.3	100 mA ... 120 A 10 mA ... 100 mA	0.2 1.0
Current CT 1000A UCT 1000.3	10 A ... 1000 A 1 A ... 10 A	0.2 1.0

Influence of external magnetic fields (45 Hz ... 66 Hz): ≤ 0.07 % / 0.5 mT ³

Temperature coefficient (TC):

Range	≤ ± TC [%/°C] ³
0° C ... +40° C	0.005
-10° C ... +50° C	0.008

Frequency / Phase Angle / Power Factor		≤ ± E
Measuring Quantity	Range	Class 0.05
Frequency (f)	40 Hz ... 70 Hz	0.01 Hz
Phase Angle (φ)	0.00 °... 359.99°	0.1 °
Power Factor (PF)	-1.000 ... +1.000	0.002

CT/PT Ratio	≤ ± E [%] ^{1 2}
Ratio error E: Sum of errors of inputs used for primary (IP, UP) and secondary (IS, US) measurements.	E _P + E _S

CT/PT Burden	≤ ± E [%] ^{1 2}
Operating burden S_n: Sum of errors of inputs used for voltage (U) and current (I) measurement.	E _U + E _I

Notes

- ¹ x.x :Related to the measuring value
x.x :Related to the measuring range final value (full scale, FS),
E(M) = FS/M * x.x (e.g. 0.1 at FS = 120 mA, E(20mA) = 120/20 * 0.1 = 0.5 %)
- ² Fundamental frequency in the range 45 ... 66 Hz
- ³ S: x.x, P, Q: x.x / PF (related to apparent power), 3- and 4-wire networks
- ⁴ E_M: Accuracy specified by manufacturer of clamp-on CT or sensor
- ⁵ Typical values, determined on the basis of monthly calibrations and calculated by least square method

Pulse Input / output Input 1 can be configured as output

Input level:	4 ... 12 VDC (24 VDC)			
Input frequency:	max. 200 kHz			
Supply:	12 VDC (I < 60 mA)			
Output level:	5V			
Pulse length:	≥ 8μs			
Meter constant: Active, Reactive, Apparent	C = C ₀ / (ln * Un) C ₀ = 60'000'000 [imp/Wh(varh, VAh)] The meter constant depends on the highest selected internal ranges ln, Un. The actual constant CPZ ₁ with unit [imp/Ws (vars, VAs)] is indicated on the display at frequency output. Internal current ranges ln [A]			
Direct 12/120 A (I1, I2, I3)	0.004	0.012	0.04	0.12
	0.4	1.2	4	12
	40	80	120	
Current CT 120A UCT 120.3	0.12	1.2	12	120
Current CT 1000A UCT 1000.3	1	10	100	1000
FLEX 3000 UCT LEM.3	30	300	3000	
	Internal voltage ranges Un [V]			
Burden U1, U2, U3	0.5	5		
Direct U1, U2, U3	60	120	240	480
	Example: Un = 240 V, ln = 12 A C = 20'833 [imp/Wh(varh, VAh)]			
Output frequency:	CPZ ₁ = C / 3'600 [imp/Ws(vars, VAs)] f ₀ = CPZ ₁ * PΣ(QΣ, SΣ) f _{max} = CPZ ₁ * 3 * Un * ln = 5.78704 imp/Ws * 3 * 240V * 12A = 50'000 [imp/s] Factor 3 for 3-phase system			